

Prostar PRC-PSW

true sinewave Inverter/Charger
Range:1-5KVA



Prostar PRC-P

Modified Sinewave Inverter/Charger
Range:0.5-5KVA



Prostar PR-K

Online Inverter/Charger
Range:1-10KVA



Inverter Specifications

Make	Model	Rated Power	Continuous Power(W)	Peak Power at 5m (W)	Norm. VDC(V)	Input Voltage range (V)	Efficiency (%)	I _{DCmax} (A)	No Load Power(W)	I _{ACmax} (A)	Dimension (LxWxH)	Weight (Kg)	
Prostar	PRC-PSW	1KVA	750	900	24	21-30	75	31.25	12	4	31x17x35	22	
		2KVA	1500	1800	24	21-30	75	62.5	31	9	40x24x43	39	
		3KVA	2250	2700	24	21-30	75	93.8	36	13	40x24x43	46	
		5KVA	3750	4500	48	2-60	75	78.13	120	22	40x28x46	77	
	PRC-P	0.5KVA	425	510	12	0.5-15	85	35.42	6	2	26x15x32	10	
		1KVA	850	1020	24	21-30	85	35.42	10	4	31x17x35	20	
		2KVA	1700	2040	24	21-30	85	70.83	26	9	40x24x43	35	
		3KVA	2550	3060	24	21-30	85	106.25	29	13	40x24x43	42	
	PRNZ	3KVA	2550	3060	48	2-60	70	75			13.6	47x20x36	30
		5KVA	3500	4200	48	2-60	70	125			22.7	47x20x36	39
	PR-K Online	1KVA	700	840	36	1.5-45	70	19.4			6	15x41x22	15
		2KVA	1400	1680	96	4-120	70	14.6			10	20x46x33	20
		3KVA	2100	2520	96	4-120	70	21.86			16	20x46x33	21
		6KVA	4200	5040	240	210-300	70	17.5			29.6	26x56x71	48
Victron Energy	C12/2000	2000W	2000	4000	12	9.5-16	93	179	12	8.6	52x26x13	12	
	C24/2000	2000W	2000	4000	24	9.5-33	94	88	13	8.6	52x26x13	12	
	C12/3000	3000W	3000	6000	12	9.5-16	93	268	15	8.6	52x26x13	18	
	C24/3000	3000W	3000	6000	24	9.5-33	94	132	15	23	37x26x22	18	
	C48/3000	3000W	3000	6000	48	8-66	95	65	16	13	37x26x22	18	
Silverline Energy	24/2000	2000W	2000	2000	24	21-32	92	94	12	13	37x26x22	18	
	48/2500	2500W	2500	3300	48	2-63	93	57	19.2	10.9	43x31x21	26	
	60/2500	2500W	2500	3300	60	51-78	94	45	18	13	43x31x21	28	
	24/3000	3000W	3000	3750	24	21-32	93	125			43x31x21	28	
	24/5000	5000W	5000	750	24	21-32	92	210	38.4	21.7	61x42x24	50	
ASP	Top Class 35/48	3500VA	3255	3900	48	2-64	93	210	24	15.6	47x32x21	30	